

**Air Mouse Keyboard
Installation & User Manual
Ver.:1.1**

Overview

Thank you for purchasing the Wireless Mini QWERTY Keyboard & Air Mouse Combo.

You can use it for emails, chat, or to enjoy your favorite games. It is compatible with HTPC, Smart TV, TV BOX running Android systems. It also supports the Sony Playstation3. Use it with your HTPC on your Sofa or browse the internet in the most comfortable fashion.

Introduction

Product overview



Package contents

- Air Mouse Keyboard
- USB Wireless Receiver
- User Manual
- USB charging cable

System Requirements

- HID compatible device
- USB port
- Windows 2000
- Windows XP
- Windows Vista, Windows CE, Windows 7
- Linux (Debian-3.1, Redhat-9.0 Ubuntu-8.10 Fedora-7.0 tested)
- Android OS (With standard USB interface)

Specifications

Receiver (dongle): Nano style

Connect port: With USB2.0 above

RF mode: 2.4Ghz GFSK

Transmission distance: Up to 10 meters

Transmission Power: Less than +4db

Power supply: Rechargeable 450mAh polymer Lithium-ion battery

Charging voltage: 4.4V ~ 5.25V

Charging current: 300mA

Sleeping Current class1: 86uA

Operation Voltage: 3.7V

Operating Current: 22mA

Product weight: 110g

Product Size: 200*58*19mm

Installation

- Open the gift box and pick up USB receiver from back cover of the keyboard.
- Insert the USB Receiver into an available USB port.
- Turn on the keyboard.

The keyboard will be found automatically. No further actions are required - you are now ready to use your keyboard!

NOTE: USB cable can be used for battery charging

Using Air mouse

Air mouse function relies on specific keys to activate. In the open status, the mouse will follow your gestures in any direction, to help you perform the moving, clicking, dragging, etc. In any status, you can use the “Lock” button to lock and unlock the Air Mouse feature.

You will enjoy more convenience and control on-screen menu easier.

Switching off the keyboard after use

After using the keyboard, push the switch to the “OFF” position. This turns off the keyboard. The USB receiver does not need to be pulled out from the PC. You can use it directly next time.

Charging the battery

The device uses built-in lithium-ion battery. Please use only approved data cables and chargers.

Note: Fully charge the unit before initial operation. This device can be used when charging, but charging time will be extended.

When the battery is low, the low-voltage light will blink to warn the user. The unit will be automatically turned off if the battery has been depleted.

Warning

- When charging finishes, pull out the charge cable.
- Never try to open or repair this product yourself.
- Keep this device away from fluids, such as water.

Maintenance

- Do not attempt to disassemble the device or replace the rechargeable battery. Doing so will void the warranty.
- The battery will discharge if it is stored for a long time without operation.
- Use the specified charger. Disconnect the device when the battery is fully charged.
- Overcharging the battery will shorten the battery life.
- Do not expose the device in extreme heat or cold environment, which will shorten the battery life.

Disposal



Always dispose the used appliance at a recycling centre. Do not dispose the used appliance together with the household waste.

Note:

Due to the device uses 2.4G radio waves technology to communicate, The connection can be subject to interference from obstacles, like walls, metals, or other electronic devices, so please keep the keyboard and dongle in a line as possible.

In line with the policy of continued development, the manufacturer reserves the right to amend The specifications without prior notification. The illustrations in the user manual are for reference only. Please operate according to the real design.